Superconducting Combined Function Magnet System for J-PARC Neutrino Beam Line

Toru Ogitsu, Yasuhiro Makida, Ken-ichi Sasaki, Tatsushi Nakamoto, Hirokatsu Ohata, Nobuhiro Kimura, Takahiro Okamura, Akio Terashima, Yasuo Ajima, Norio Higashi, Takayuki Tomaru, Masahis Iida, Kenichi Tanaka, Osamu Araoka, Shoji Suzuki, Akira Yamamoto, Takashi Kobayashi, Atsuko Ichikawa, Takeshi Nakadaira, Ken Sakashita, Takuya Hasegawa, Yoshiaki Fujii, Hidekazu Kakuno

Contents

- **Introduction**
- Superconducting Combined Function Magnet
  - Magnet & System Overview
  - Prototype Development
  - Mass Production & Installation
- Commissioning
  - Hardware Commissioning
  - Beam Commissioning
- Conclusion

Tokai-to-Kamioka (T2K) long baseline neutrino oscillation experiment



Super-Kamiokande
(ICRR, Univ. Tokyo)

J-PARC Main Ring
(KEK-JAEA, Tokai)

ν_e appearance (θ_{13})



- Goal
  - **Discover νe app.**
  - νμ disapp. meas.
- Intense narrow spectrum νμ beam from J-PARC MR
  - Off-axis w/ 2~2.5deg
  - Tuned at osci. max.
- SK: largest, high PID performance




Linac
180→400 MeV
J-PARC Facility
(KEK/JAEA)
South to North
3 GeV RCS
3GeV, 25 Hz, 1MW
Neutrino Beams
(to Kamioka)
Materials and Life
Experimental
Facility
Main ring: 30 GeV,
0.3 Hz, 0.75 MW→ 1.66 MW
JFY2007 Beams
JFY2008 Beams
JFY2009 Beams
Hadron Exp.
Facility
Bird's eye photo in January of 2008

Neutrino beamline

Neutrino monitor build.

Electromagnetic horn



Graphite target



UA1 magnet



Beam dump



Decay volume



Target station

Primary proton beam line

Primary Beam-line

Assumed Beam Loss
750W@Prep.
250W@FF.
(1W/m @ ARC)



20D+20Q > 28 SCFM

Optimize Cost & Schedule

edule

Contents

- Introduction
- **Superconducting Combined Function Magnet**
  - **Magnet & System Overview**
  - Prototype Development
  - Mass Production & Installation
- Commissioning
  - Hardware Commissioning
  - Beam Commissioning
- Conclusion

SC Combined Function Magnet

E.M. Design:
Single layer CFM

Mech. Design:
Plastic Spacer, Keyed Yoke, SUS304L Shell







S.C. Cable for LHC-Dipole-Outer (strand: LHC leftover) w/ MQXA Insulation

Specification





Coil ID.:	173.4mm	Op. Current:	7345 A
Mag. Length:	3300 mm	Op. Margin:	72%
Mech. Length:	3630 mm	Inductance:	14.3 mH
Tmax:	< 5.0K	Stored Energy:	386 kJ
(Supercritical Helium Cooling)		# of Magnet:	28
Dipole Field:	2.59 T	SC Cable:	NbTi/Cu
Quad. Field:	18.6 T/m		Rutherford Type Cable
Field Error:	< 10^-3 @ 50mm		for LHC Dipole Outer-L

	3D-SS	3D-LE	3D-RE	3D-Integral
Lmag(m)	1.94	0.78	0.58	3.3
Bl (T)	2.591	2.602	2.603	2.601
b2(unit)	3.628	3.567	3.517	3.581
b3(unit)	-0.93	-5.81	-10.15	-3.37
b4(unit)	5.01	-1.11	-2.35	-2.3
b5(unit)	2.07	-8.9	-1.60	-3.5
b6(unit)	-6.36	-7.9	-9.8	-7.2
b7(unit)	-1.16	-3.5	-5.3	-2.4
b8(unit)	-3.95	-2.9	-3.6	-3.7
b9(unit)	-8.86	-7.7	-7.9	-8.4
b10(unit)	-0.25	0.3	0.3	-0.0
b11(unit)	-3.10	-2.7	-2.6	-2.9
b12(unit)	2.07	1.7	1.6	1.9

- Peak field at conductor in straight section is 4.6 T at 50 GeV.
- Load line ratios at 5 K for 40 & 50 GeV are 58 % & 72 %, respectively.
- Field quality within a tolerance of 10^{-3} is acceptable.

Good Not So Good Enough

System Overview



- 14 Doublets
- 13 Interconnets
  - 4 Profile Monitors
  - 5 Position Monitors
  - 3 Steering Magnets
  - 4 Quench Valves

ostat









cryostat: Reduce Cost and Risk

- Common Parts ➔advantage of LHC mass production

Interconnects



Corrector Interconnect



Quench Relief Valve

Refrigeration System



Contents

- Introduction
- **Superconducting Combined Function Magnet**
  - Magnet & System Overview
  - **Prototype Development**
  - Mass Production & Installation
- Commissioning
  - Hardware Commissioning
  - Beam Commissioning
- Conclusion



Coil & Collar

- Off-center magnetic pole ⇨ Left-right asymmetry
- Different thickness of wedges for both sides ⇨ Asymmetric mech. property
- Cured with wedges and the pole spacer ⇨ No collar insertion





For excitation : ~30 MPa

For cool down : ~20 MPa ⇨ 50 MPa required

⇨ **Pre-stress of 80 MPa given by Yoking Process**

⇨ **Coil over-size of 0.7 mm & 1.0 mm**

GFRP Wedges and Spacers





• End spacers: G10 (CNC file)

• Ramp box: G10

• Wedges: G11

Size Tolerance

Target: < 0.05 mm

Actual: 0.1 mm

*Coil Pre-stress tolerance after yoking:
50 MPa < Coil Prestress < 100 MPa

Verified by practice coil winding and mechanical short model study

Coil Winding Tool





Coil Winding for Prototype Magnet











Mirror-symmetry Top & Bottom coils of the prototype

- Coil with pre-pregnant Epoxy resin cured at 400K for 5 hours.
- Asymmetric coil oversize determined by 2 sets of shims.

Coil Size Measurement





Cured bottom coil on the mandrel. Several sets of strain gauges are installed on the press-bars in both sides to measure coil stress during the coil size measurement.

Coil Size Measurement





Cured bottom coil on the mandrel. Several sets of strain gauges are installed on the press-bars in both sides to measure coil stress during the coil size measurement.

Coil Size Measurement





Cured bottom coil on the mandrel. Several sets of strain gauges are installed on the press-bars in both sides to measure coil stress during the coil size measurement.

Expected pre-stress of 60-80 MPa after magnet assembly is similar to the design value of 80 MPa.

Plastic Collar



Compression Molding

@430 K, 10 min.

&

Post-curing w/ Forming Jig

@ 450K, 10hrs

Glass-reinforced Phenolic Thermosets
Rin=102 mm, t=20 mm, L= 100 mm
*PM9640 supplied by Sumitomo Bakelite, and fabricated by Arisawa

Size control is very important!!

- R&D to search the most appropriate condition needs 18 months.
- Molding jig was designed with taking into account the consistent deformation.
  - *Maximum Deformation: 0.1-0.2mm*
  - *Std. Deviation: ~50 μm*



Yoking
-Coil Installation-







Yoking -Top Assembly Installation-

Top Collar Installation



Top Yoke Installation

Top lead Collar Installation



Top Yoke Installation Complete

Yoking -Press-



Yoking -Keying-

Key pushing

Key Insertion

Complete

Shell Welding

Longitudinal shell welding by a set of two automated welding machines.





Final Assembly

End-ring welding

Installation of the alignment target

Leads connection by soldering.

Excitation Test of the 1st Prototype

I_{op} = 7345 A @ 50 GeV (and I_{max} = 7,700 A) reached with no quench, on March 4, 2005



Participating member

Participating members



Installation into cryostat,

	Measurement	*Computation*
Current (A)	7460	7345
B_1 (T•m)	8.906	8.712
B_2 (T•m)	3.127	3.120
B_3 (T•m)	$-220.6*10^{-4}$	$-293.6*10^{-4}$
B_4 (T•m)	$-5.9*10^{-4}$	$-20.1*10^{-4}$
B_5 (T•m)	$-51.9*10^{-4}$	$-30.6*10^{-4}$
B_6 (T•m)	$-75.2*10^{-4}$	$-62.8*10^{-4}$
B_7 (T•m)	$-44.6*10^{-4}$	$-20.9*10^{-4}$
B_8 (T•m)	$-74.5*10^{-4}$	$-32.0*10^{-4}$
B_9 (T•m)	$-79.9*10^{-4}$	$-73.4*10^{-4}$
B_{10} (T•m)	$-13.8*10^{-4}$	$-0.3*10^{-4}$

Field Measurement Result



Record of Excitation current

Contents

- Introduction
- **Superconducting Combined Function Magnet**
  - Magnet & System Overview
  - Prototype Development
  - **Mass Production & Installation**
- Commissioning
  - Hardware Commissioning
  - Beam Commissioning
- Conclusion



Magnet Mass Production

- Mass production
  - bidding won by Mitsubishi Electric
  - Built to Print Contract
- Major Monitoring Data
  - Coil Length, Prestress
  - Yoke size
  - Shell size
  - Warm Field Quality
- Cold Test at KEK



Coil Prestress Measurement Results



Average: ~90 Mpa

Standard Deviation: ~7 Mpa

Equivalent Coil Size Deviation

High Field Side: 0.07 mm (0.13 mrad)

Low Field Side: 0.14 mm (0.26 mrad)

MQXA (LHC IRQ)

Inner Coil Size Deviation: 0.022 mm (0.1 mrad)

Warm Field Measurement







$R_{ref} = 50$ mm

B1

B1 Average: -1.184 Tm/kA ;
B2 Average: 0.4278 Tm/kA
= Q/B: 0.36
Good For Optics

B1 Standard Deviation:
22.56E-4 Tm/kA
= ΔX 0.3 mm
Acceptable



WMFM Results

R_{ref} = 50 mm

A1

A1 Average: -42.22e-4 Tm/kA ;
= ΔY 0.5 mm
A1 Standard Deviation:
17.25E-4 Tm/kA
= Δ 0.2 mm
Acceptable



A2 Standard Deviation:
2.57E-4 Tm/kA
= Δθ 0.5 mrad
Angle Standard Deviation:
= Δθ 0.7 mrad
Acceptable



Higher Harmonics

Influence to Field Quality by Coil Prestress

| | | |

Corrector Production

Manufactured and Tested at BNL

Direct Winding on Copper Bobbinn

Cold test for Quench Performance

Warm MFM for Integral Field Quality





Parameter	Average Value	Std. Dev.
B1 Integral	2.34 Tm/kA	$22.4 \cdot 10^{-4}$ Tm/kA
A1 Integral	2.32 Tm/kA	$32.3 \cdot 10^{-4}$ Tm/kA
B1-A1 angle	-1.4 mrad	2.2 mrad

Installation
Completed by
Dec. 2008

Contents

- Introduction
- Superconducting Combined Function Magnet
  - Magnet & System Overview
  - Prototype Development
  - Mass Production & Installation
- **Commissioning**
  - **Hardware Commissioning**
  - Beam Commissioning
- Conclusion

Refrigerator Test & Magnet Cool Down

- Refrigerator Test in Dec.
  - Refrigeration Power ~ 1.5kW
- Cool Down Magnet By about 10 days



Pressure Drop

--steady state mode (230 g/sec ~ 330 g/sec)--



- Pressures at Cernox sensors can be obtained from above figure.
- Wall Friction Coefficient, λ, is treated as adjustable parameter.

Heat Load



- Magnet String
  - 140 W
- Transfer Line
  - 50 W
- Current Lead
  - 60 W @ 0 flow
  - 0 W @ 70 L/min
  - 100 L/min @ 4kA



Quench Protection Test

- Performance test of quench protection system
  - Heater Induced Quench
  - Quench Recovery

Cold Diode



MSS (Magnet Safety System)


D
F
D
F
8kA CL
8kA CL
Extraction Circuit
8kA 30V
trigger
trigger
• Quench Protection Heater
– Powered by Capacitor Bank
• Cold Diode
– Turn On Voltage: 6V
– Forward Voltage: 1V
• Quench Detector
dapnia
saclay
Board 3
Board 3_4 (redundancy)
Board 4
Detection
Cryostat 3
Cryostat 4
Current
Beam
Magnet D
Magnet F
Magnet D
Magnet F
= Junction
2006, March 7th
CEA DSM Dapnia SIS - Jean-Paul Charrier - T2K MSS - Preliminary Definition
• Dump Circuit
– Protect Cold Diodes and SC Bus Bars
– Time Constant: 20 sec
Quench Protection Test

Bypass Diode Test



Cool Down after Quench

- Quench Test at 4400A (30GeV nominal)
  - Normal case (4 magnets) : ~2 hour to recover

Good noise reduction by MSS

↓

No false quench detection by system shut down

↓

Avoid extra magnet to quench

↓

Save time for quench recovery



Contents

- Introduction
- Superconducting Combined Function Magnet
  - Magnet & System Overview
  - Prototype Development
  - Mass Production
- **Commissioning**
  - Hardware Commissioning
  - **Beam Commissioning**
- Conclusion

T2K beamline started operation!

FIRST SHOT after turning on SC magnets at 19:09, Apr.23, 2009

Beam profile monitor signal





First observation of muons produced in neutrino beamline

T2K beamline started operation!

MR intensity



After ~10 shots for tuning, proton beam hit around target center

Muon monitor signal



Proton beam profile monitor along nu beamline



Muon monitor profile



OTR detector just in front of target (fluorescence plate)



Horn 250kA

Optics Study

- SC Magnet current dependence
  - Beam induced quench eventually




Beam Position X
SC 4436 A
SC 4406 A
SC 4376 A
SC 4360 A
SC 4350 A
SC 4320 A
SC 4280 A
SC 4240 A
SC 4200 A
SC 4160 A
40
30
20
10
0
-10
-20
1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19
SC Part
SC 4436 A
SC 4406 A
SC 4376 A
SC 4360 A
SC 4350 A
SC 4320 A
SC 4280 A
SC 4240 A
SC 4200 A
SC 4160 A
5
4
3
2
1
0
-1
-2
-3
-4
-5
1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19
Beam Position Y


Beam Size X
SC 4436 A
SC 4406 A
SC 4376 A
SC 4360 A
SC 4350 A
SC 4320 A
SC 4280 A
SC 4240 A
SC 4200 A
SC 4160 A
Beam Size Y
SC Part

Beam Induce

Partial beam loss observed at 4200

- At around SCR2~SCR4

Full beam loss observed at 4160 A

- Beam loss in between SCR2 ~ SCR4
- Quench at SCR3F
- No damage observed







Contents

- Introduction
- Superconducting Combined Function Magnet
  - Magnet & System Overview
  - Prototype Development
  - Mass Production & Installation
- Commissioning
  - Hardware Commissioning
  - Beam Commissioning
- **Conclusion**

Conclusion

- **A SCFM with Single Layer Coil Winding is Developed**
- **Good Cost & Time Saving with Optimum Condition**
  - Half Cell = one SCFM; Dipole > Quadrupole
- Draw back
  - D/Q ratio fixed **➔ It appears to be OK**
- International Collaboration
  - BNL, Saclay, CERN
- Construction Completed on Schedule
- Commissioning
  - No major problem with hardware commissioning
    - Minor problem associate with corrector current lead
      - scheduled to be fixed in this summer
  - Beam Commissioning went smoothly
    - Beam went through SC arc with the first attempt
    - Beam behaved as expected (almost)
    - Beam induced quench > quench protection works OK

Application of SCFM 1

- **Good Cost & Time Saving with Optimum Condition**
  - **Half Cell = one SCFM**
  - Dipole > Quadrupole
- For Beam Line
  - Already good enough?
    - So far so good.
- For Accelerator Ring
  - Needs more study on field quality
    - Neutrino production magnets show good reproducibility

    = there are some hope
- Special Accelerator
  - Muon Acceleration FFAG?



Application of SCFM 2

- **Good Cost & Time Saving with Optimum Condition**
  - Half Cell = one SCFM
  - **Dipole > Quadrupole**
- For Beam Line
  - Already good enough?
    - So far so good
- For Accelerator Ring
  - Needs more study on field quality
    - Neutrino production magnets show good reproducibility

    = there are some hope
- Special Accelerator
  - Muon Acceleration FFAG?



Application of SCFM 3

- A SCFM with Single Layer Coil Winding is Developed
- Good Cost & Time Saving with Optimum Condition
  - Half Cell = one SCFM
  - Dipole > Quadrupole
- **For Beam Line**
  - **Already good enough?**
    - **So far so good**
- **For Accelerator Ring**
  - **Needs more study on field quality**
    - **Neutrino production magnets show good reproducibility**

    = there are some hope
- **Special Accelerator**
  - **Muon Acceleration FFAG?**



Acknowledgment

2~3T 0.4m-dia 7m-long
Solenoid for Muon Transport



s in



Super Qs

SuperOMEGA

J-PARC g-2

3T 3m-dia 3m-long
Solenoid for Muon Storage





COMET

Thank you very much

for your listening



JFY 2001 : 10 Cell FODO

20 Dipole + 20 Quads = 40 Magnets



Ichikawa w/ help Doornbos



Dipole: 4T*3m



Quadrupole: 36T/m*0.9m

Optics with 14 Doublets





- Arc Section Optics
  - 14 doublets; 28 SCFM
- Optimized Collimator in Prep. Sec.
  - Minimize risk to Arc Section

Ichikawa, Iwamoto, Tanabe
w/ help Doornbos, Noumi, Oide

Cold Diode

- Influence of Neutron to Cold Diode
  - Intensively studied at CERN by D. Hagedorn
    - Change Forward Voltage
  - Using LHC Arc Quad Assembly
    - 7.5kA Operation
    - Limit; 2• 10^{14} n/cm^2





Courtesy D.Hagdorn

LHC&J-PARC Neutrino SC System

- **Comparison**
  - Size 27km vs 150m
  - Number of Magnets ~5000? Vs 28
  - Inductance and Stored Energy
    - LHC (1 sector) : 15.1H, 1.2GJ
    - J-PARC: 0.4H, 10MJ(50GeV), 5MJ(30GeV)
  - Helium Inventory
    - LHC(overall) : 56万Nm^3
    - J-PARC: 4000Nm^3

Combined Function Magnet Concept









Current Distribution



2002 Spring
Proposed by BNL
RHIC DX +
Direct winding coil

OR







2002 Summer
Proposed by T.O.
L-R Asymmetry Coil
Based on FFAG SCM